

BA-7218PC-2

SIZE: 18'-0"L X 8'-6"H X 10"D

POWER: 120 VAC, 60 Hz., 1-PHASE  
354 WATTS.

CONTROL CONSOLE: MP-80 SERIES CONTROLLER.


LEDs: AMBER LED.

OPTIONS: LIGHTNING DAMAGE REDUCTION UNIT.

ESTIMATED WEIGHT: 772 LBS.

GENERAL NOTES:

- \* REFERENCE 01-0500-01 FOR INSTALLATION NOTES.
- \* POWER REQUIREMENTS ARE VALID FOR 90 DAYS AFTER THE ORIGINAL RELEASE OR BY THE MOST RECENT REVISION OF THE DRAWING.



BA-7218PC-2  
(18"H DIGITS MOVED TO THE ENDS OF PITCH COUNT SECTION, ADDED TRIM)

CUSTOMER APPROVAL:		MY SIGNATURE BELOW SIGNIFIES MY APPROVAL TO PROCEED WITH THE DESIGN WORK SPECIFIED HEREIN AND ACKNOWLEDGEMENT THAT I HAVE RECEIVED AND READ THE INSTALLATION SPECIFICATIONS CONTAINED IN FAIR-PLAY DOCUMENT NO. 01-0500-01. CONSULT YOUR FAIR-PLAY SALES ASSOCIATE IF YOU SHOULD HAVE ANY QUESTIONS OR REQUIRE ANY CHANGES TO THIS DOCUMENT.	
PROJECT:	SIGNATURE:	DATE:	
REFERENCE #:	PRINT NAME:		

<b>FAIR-PLAY</b>	THIS DOCUMENT CONTAINS FAIR-PLAY PROPRIETARY INFORMATION. ANY DISCLOSURE, USE OR DUPLICATION OF THE DOCUMENT OR OF ANY INFORMATION CONTAINED THEREIN FOR OTHER THAN THE SPECIFIC PURPOSE FOR WHICH IT WAS DISCLOSED IS EXPRESSLY PROHIBITED, EXCEPT AS MAY BE OTHERWISE AGREED TO IN WRITING. COPYRIGHT 2019.			
	TITLE	DRAWN BY	MODEL	
	FACE VIEW FOR BA-7218PC-2	BEW	B	BA-7218PC-2
		DATE	DWG. NO.	
6110 AVIATOR DRIVE HAZELWOOD, MO 63042	02-05-18	01-7218-45-1		
	SCALE			
	3/8"=1'-0"			

REV.#	CHANGE	DATE	BY
B	UPDATED TITLE BLOCK FORMAT	03-09-21	BEW
A	CHANGED FROM MP-70 TO MP-80 CONTROL	10-10-18	BEW
OR	ORIGINAL RELEASE	02-05-18	BEW