

FB-8136-2

SIZE: 36'-0" L X 10'-0" H X 10" D

POWER: 120 VAC, 60 Hz., 1-PHASE  
1,121 WATTS.

120 VAC AT THE CONTROL LOCATION.

CONTROL CONSOLE: MP-70 SERIES CONTROLLER.

CONTROL CABLE: 22GA 2-WIRE SHIELDED.

(IF WIRELESS ORDERED, CABLE NOT REQ'D.)

LEDs: AMBER LED.

OPTIONS: MODEL HC-70 CLOCK HAND SWITCH FOR SECOND OPERATOR.  
(CLOCK START/STOP AND CLOCK RESET.)

MODEL F600-70 SIDELINE CLOCK HAND SWITCH CONTROL  
WITH SPLIT TIME.

MODEL F650-70 CLOCK HAND SWITCH CONTROL.

LIGHTNING REDUCTION UNIT.


OPTIONAL MP-70 CONTROL OPERATION.

ACTUAL WEIGHT: 1,618 LBS.

GENERAL NOTES:

\* REFERENCE 01-0500-01 FOR INSTALLATION NOTES.

\* POWER REQUIREMENTS ARE VALID FOR 90 DAYS AFTER THE ORIGINAL  
RELEASE OR BY THE MOST RECENT REVISION OF THE DRAWING.



FB-8136-2

CUSTOMER APPROVAL:		MY SIGNATURE BELOW SIGNIFIES MY APPROVAL TO PROCEED WITH THE DESIGN WORK SPECIFIED HEREIN AND ACKNOWLEDGEMENT THAT I HAVE RECEIVED AND READ THE INSTALLATION SPECIFICATIONS CONTAINED IN FAIR-PLAY DOCUMENT NO. 01-0500-01. CONSULT YOUR FAIR-PLAY SALES ASSOCIATE IF YOU SHOULD HAVE ANY QUESTIONS OR REQUIRE ANY CHANGES TO THIS DOCUMENT.	
PROJECT:	SIGNATURE:	DATE:	
REFERENCE #:	PRINT NAME:		

REV.#	CHANGE	DATE	BY
F	UPDATED TITLE BLOCK FORMAT	09-21-21	BEW
E	ADDED POWER NOTE	04-10-12	BEW
D	GENERAL UPDATES	04-26-11	BEW
C	UPDATED CLOCK DIGITS	06-17-09	RMS
B	GENERAL UPDATES	09-25-07	BEW
A	ADDED MODEL #	2/17/04	NAP
OR	ORIGINAL RELEASE	11-20-03	BEW

	THIS DOCUMENT CONTAINS FAIR-PLAY PROPRIETARY INFORMATION. ANY DISCLOSURE, USE OR DUPLICATION OF THE DOCUMENT OR OF ANY INFORMATION CONTAINED THEREIN FOR OTHER THAN THE SPECIFIC PURPOSE FOR WHICH IT WAS DISCLOSED IS EXPRESSLY PROHIBITED, EXCEPT AS MAY BE OTHERWISE AGREED TO IN WRITING. COPYRIGHT 2019.	
	TITLE <b>FACE VIEW FOR FB-8136-2</b>	DRAWN BY BEW
	DATE 11-20-03	MODEL B FB-8136-2
	SCALE 1/4"=1'-0"	DWG. NO. 01-8136-55-1
6110 AVIATOR DRIVE HAZELWOOD, MO 63042		