

BA-7218-2

BA-7218-2

SIZE: 18'-0"L X 6'-6"H X 10"D

POWER: 120 VAC, 60 Hz., 1-PHASE

287 WATTS.

CONTROL CONSOLE: MP-80 SERIES CONTROLLER.

LEDs: AMBER LED.

OPTIONS: LIGHTNING DAMAGE REDUCTION UNIT.

ESTIMATED WEIGHT: 622 LBS.

GENERAL NOTES:

* REFERENCE 01-0500-01 FOR INSTALLATION NOTES.

* POWER REQUIREMENTS ARE VALID FOR 90 DAYS AFTER THE ORIGINAL RELEASE OR BY THE MOST RECENT REVISION OF THE DRAWING.

CUSTOMER APPROVAL:	I HAVE RECEIVED AND READ THE INSTALLATION SI	D PROCEED WITH THE DESIGN WORK SPECIFIED HEREIN AND ACKNOWLEDGEMENT THAT PECIFICATIONS CONTAINED IN FAIR-PLAY DOCUMENT NO. 01-0500-01. CONSULT YOUR VE ANY QUESTIONS OR REQUIRE ANY CHANGES TO THIS DOCUMENT.
PROJECT:	SIGNATURE:	DATE:
REFERENCE #:	PRINT NAME:	

FAIR-PLAY

THIS DOCUMENT CONTAINS FAIR-PLAY PROPRIETARY INFORMATION. ANY DISCLOSURE, USE OR DUPLICATION OF THE DOCUMENT OR OF ANY INFORMATION CONTAINED THEREIN FOR OTHER THAN THE SPECIFIC PURPOSE FOR WHICH IT WAS DISCLOSED IS EXPRESSLY PROHIBITED, EXCEPT AS MAY BE OTHERWISE AGREED TO IN WRITING. COPYRIGHT 2022.

FACE VIEW FOR
BA-7218-2

6110 AVIATOR DRIVE
HAZELWOOD, MO 63042

DRAWN BY		MODEL
RMS	\square	DA 7010 0
DATE		BA-7218-2
11-14-08	DWG.	NO
SCALE	ا ما	
1/2"=1'-0"	\cup	-7218 - 01 -

O	UPDATED TITLE BLOCK FORMAT	07-28-22	BEW
O	GENERAL UPDATES, TITLE BLOCK, FROM MP-70 TO MP-80	12-09-19	BEW
В	ADDED POWER NOTE	03-28-12	BEW
A	GENERAL UPDATES	03-29-11	BEW
OR	ORIGINAL RELEASE	11-14-08	RMS
REV.#	CHANGE	DATE	BY