

PSO-6900-2

SIZE: 4'-0"L X 2'-6"H X 8"D

POWER: 120 VAC, 50/60 Hz., 1-PHASE
37 WATTS.

CONTROL CONSOLE: MP-70 SERIES CONTROLLER.
CONTROL CABLE: 22GA 2-WIRE SHIELDED.

LEDs: AMBER LED.

COMES WITH TRAVEL CART (62-0000-05)


OPTIONS: HORN KIT. (12-0010-06)

BATTERY KIT, FACTORY INSTALLED ONLY, RUN TIME 6 HOURS. (12-0010-04)

WIRELESS BATTERY KIT, FACTORY INSTALLED ONLY. (16-0019-03)

ESTIMATED WEIGHT: 50 LBS. (120 VAC)
65 LBS. (WITH BATTERY)

- GENERAL NOTES:
- * REFERENCE 01-0500-01 FOR INSTALLATION NOTES.
 - * POWER REQUIREMENTS ARE VALID FOR 90 DAYS AFTER THE ORIGINAL RELEASE OR BY THE MOST RECENT REVISION OF THE DRAWING.



PSO-6900-2

CUSTOMER APPROVAL:		MY SIGNATURE BELOW SIGNIFIES MY APPROVAL TO PROCEED WITH THE DESIGN WORK SPECIFIED HEREIN AND ACKNOWLEDGEMENT THAT I HAVE RECEIVED AND READ THE INSTALLATION SPECIFICATIONS CONTAINED IN FAIR-PLAY DOCUMENT NO. 01-0500-01. CONSULT YOUR FAIR-PLAY SALES ASSOCIATE IF YOU SHOULD HAVE ANY QUESTIONS OR REQUIRE ANY CHANGES TO THIS DOCUMENT.	
PROJECT:	SIGNATURE:	DATE:	
REFERENCE #:	PRINT NAME:		

FAIR-PLAY	THIS DOCUMENT CONTAINS FAIR-PLAY PROPRIETARY INFORMATION. ANY DISCLOSURE, USE OR DUPLICATION OF THE DOCUMENT OR OF ANY INFORMATION CONTAINED THEREIN FOR OTHER THAN THE SPECIFIC PURPOSE FOR WHICH IT WAS DISCLOSED IS EXPRESSLY PROHIBITED, EXCEPT AS MAY BE OTHERWISE AGREED TO IN WRITING. COPYRIGHT 2022.			
	TITLE	DRAWN BY	B	MODEL
	FACE VIEW FOR PSO-6900-2	BEW		
		6110 AVIATOR DRIVE HAZELWOOD, MO 63042	DATE	DWG. NO.
		09-25-07	01-6900-03-1	
		SCALE		
		1/8"=1"		

C	UPDATED TITLE BLOCK FORMAT	08-19-22	BEW
B	GENERAL UPDATES, ADDED POWER NOTE	04-25-12	BEW
A	GENERAL UPDATES	05-05-11	BEW
OR	ORIGINAL RELEASE	09-25-07	BEW
REV.#	CHANGE	DATE	BY