

BA-7136PC-2

SIZE: 36'-0"L X 13'-0"H X 10"D

POWER: 120 VAC, 60 Hz., 1-PHASE
950 WATTS.

CONTROL CONSOLE: MP-80 SERIES CONTROLLER.


LEDs: AMBER LED.

OPTIONS: LIGHTNING REDUCTION UNIT.

ESTIMATED WEIGHT: 1,989 LBS.

GENERAL NOTES:

- * REFERENCE 01-0500-01 FOR INSTALLATION NOTES.
- * POWER REQUIREMENTS ARE VALID FOR 90 DAYS AFTER THE ORIGINAL RELEASE OR BY THE MOST RECENT REVISION OF THE DRAWING.



BA-7136PC-2
(24"H DIGITS MOVED TO THE ENDS OF PITCH COUNT SECTION, ADDED TRIM)

CUSTOMER APPROVAL:		MY SIGNATURE BELOW SIGNIFIES MY APPROVAL TO PROCEED WITH THE DESIGN WORK SPECIFIED HEREIN AND ACKNOWLEDGEMENT THAT I HAVE RECEIVED AND READ THE INSTALLATION SPECIFICATIONS CONTAINED IN FAIR-PLAY DOCUMENT NO. 01-0500-01. CONSULT YOUR FAIR-PLAY SALES ASSOCIATE IF YOU SHOULD HAVE ANY QUESTIONS OR REQUIRE ANY CHANGES TO THIS DOCUMENT.	
PROJECT:	SIGNATURE:	DATE:	
REFERENCE #:	PRINT NAME:		

FAIR-PLAY	THIS DOCUMENT CONTAINS FAIR-PLAY PROPRIETARY INFORMATION. ANY DISCLOSURE, USE OR DUPLICATION OF THE DOCUMENT OR OF ANY INFORMATION CONTAINED THEREIN FOR OTHER THAN THE SPECIFIC PURPOSE FOR WHICH IT WAS DISCLOSED IS EXPRESSLY PROHIBITED, EXCEPT AS MAY BE OTHERWISE AGREED TO IN WRITING. COPYRIGHT 2019.		
	TITLE	DRAWN BY	MODEL
	FACE VIEW FOR BA-7136PC-2	BEW	B BA-7136PC-2
		DATE 02-05-18	DWG. NO. 01-7136-143-1
	SCALE 1/4"=1'-0"		

REV.#	CHANGE	DATE	BY
C	UPDATED TITLE BLOCK FORMAT	03-16-20	BEW
B	CHANGED CONTROL TO MP-80	07-27-18	BEW
A	CHANGED PC SECTION FROM 2'-6"H TO 3'-0"H	04-11-18	BEW
OR	ORIGINAL RELEASE	02-05-18	BEW

6110 AVIATOR DRIVE
HAZELWOOD, MO 63042