

BA-7116PC

SIZE: 16'-0"L X 9'-6"H X 10"D

POWER: 120 VAC, 60 Hz., 1-PHASE
398 WATTS.

120 VAC AT THE CONTROL LOCATION.


CONTROL CONSOLE: MP-70 SERIES CONTROLLER.
CONTROL CABLE: 22GA 2-WIRE SHIELDED.
(IF WIRELESS ORDERED, CABLE NOT REQ'D.)

LEDs: AMBER LED.

OPTIONS: WIRELESS MP-70 CONTROL OPERATION.

ESTIMATED WEIGHT: 646 LBS.

GENERAL NOTES:
* REFERENCE 01-0500-01 FOR INSTALLATION NOTES.
* POWER REQUIREMENTS ARE VALID FOR 90 DAYS AFTER THE ORIGINAL
RELEASE OR BY THE MOST RECENT REVISION OF THE DRAWING.



BA-7116PC
(24"H DIGITS MOVED TO THE ENDS OF PITCH COUNT SECTION, ADDED TRIM)

CUSTOMER APPROVAL:		MY SIGNATURE BELOW SIGNIFIES MY APPROVAL TO PROCEED WITH THE DESIGN WORK SPECIFIED HEREIN AND ACKNOWLEDGEMENT THAT I HAVE RECEIVED AND READ THE INSTALLATION SPECIFICATIONS CONTAINED IN FAIR-PLAY DOCUMENT NO. 01-0500-01. CONSULT YOUR FAIR-PLAY SALES ASSOCIATE IF YOU SHOULD HAVE ANY QUESTIONS OR REQUIRE ANY CHANGES TO THIS DOCUMENT.	
PROJECT:	SIGNATURE:	DATE:	
REFERENCE #:	PRINT NAME:		

FAIR-PLAY	THIS DOCUMENT CONTAINS FAIR-PLAY PROPRIETARY INFORMATION. ANY DISCLOSURE, USE OR DUPLICATION OF THE DOCUMENT OR OF ANY INFORMATION CONTAINED THEREIN FOR OTHER THAN THE SPECIFIC PURPOSE FOR WHICH IT WAS DISCLOSED IS EXPRESSLY PROHIBITED, EXCEPT AS MAY BE OTHERWISE AGREED TO IN WRITING. COPYRIGHT 2022.			
	TITLE	DRAWN BY	B	MODEL
	FACE VIEW FOR BA-7116PC	BEW		
		DATE	DWG. NO.	
6110 AVIATOR DRIVE HAZELWOOD, MO 63042	07-08-26	1/2"=1'-0"	01-7116-10-1	

OR	ORIGINAL RELEASE	07-08-26	BEW
REV.#	CHANGE	DATE	BY